

## SIMPLEX TYPE



SC PC



SC APC



LC PC



E2000 APC



FC PC

## DUPLEX TYPE



SC PC



SC APC



LC PC



E2000 APC

SL.NO	PARAMETERS	TYPES OF ADAPTER				
		SCPC Simplex/Duplex	FCPC	SCAPC Simplex/Duplex	LCPC Simplex/Duplex	E2000APC Simplex/Duplex
1	Insertion Loss	≤-0.10 dB	≤-0.10 dB	≤-0.10 dB	≤-0.10 dB	≤-0.10 dB
2	Sleeve	Zirconia Ceramic	Zirconia Ceramic	Zirconia Ceramic	Zirconia Ceramic	Zirconia Ceramic
3	Adapter Material	Plastic-Blue	Ni-Cr Plated Brass	Plastic-Green	Plastic-Blue	Thermoplastic-Green
4	Mounting	Clip/Screw	Screw	Clip/Screw	Clip	Clip and Screw
5	Reference Specifications	TEC spec GR/OFJ-01/04.April 2004 for FC and GR/OFJ-02/01.May 2004 for FC				IEC spec IEC 61753-1
6	Mating Test	Conduct 500 cycle mating test at each sides and measured insertion loss must be within specification after test				

### Note:

1. Ensure packed parts are free from dust, and proper care should be taken to avoid any kind of damages, also ensure necessary accessories before packing.
2. Adapters must operate freely while assembling, and no damages, cracks or rust are allowed near locking latches.
3. Mention actual insertion loss in report/affix sticker.
4. Additional requirements if any will be mentioned in purchase order.
5. Ensure all visual, Testing and Functional parameters are taken care.
6. Special tools required if any for handling and maintenance shall be clearly indicated and supplied.
7. Ensure availability of sufficient information to alert potential hazard, also indicate required precautions and working practice.